Order this document
by BC182/D

Amplifier Transistors

NPN Silicon

BC182,A,B
BC183
BC184





CASE 29–04, STYLE 17
TO–92 (TO–226AA)

MAXIMUM RATINGS

Rating	Symbol	BC 182	BC 183	BC 184	Unit
Collector–Emitter Voltage	V_{CEO}	50	30	30	Vdc
Collector–Base Voltage	V_{CBO}	60	45	45	Vdc
Emitter–Base Voltage	V_{EBO}	6.0			Vdc
Collector Current — Continuous	I_C	100			mAdc
Total Device Dissipation @ T_A = 25°C Derate above 25°C	P_D	350 2.8			mW mW/°C
Total Device Dissipation @ T_C = 25°C Derate above 25°C	P_D	1.0 8.0			Watts mW/°C
Operating and Storage Junction Temperature Range	T_J, T_{stg}	–55 to +150			°C

THERMAL CHARACTERISTICS

Characteristic	Symbol	Max	Unit
Thermal Resistance, Junction to Ambient	$R_{\theta JA}$	357	°C/W
Thermal Resistance, Junction to Case	$R_{\theta JC}$	125	°C/W

ELECTRICAL CHARACTERISTICS (T_A = 25°C unless otherwise noted)

Characteristic		Symbol	Min	Typ	Max	Unit
OFF CHARACTERISTICS						
Collector–Emitter Breakdown Voltage (I_C = 2.0 mA, I_B = 0)		$V_{(BR)CEO}$				V
	BC182		50	—	—	
	BC183		30	—	—	
	BC184		30	—	—	
Collector–Base Breakdown Voltage (I_C = 10 μA, I_E = 0)		$V_{(BR)CBO}$				V
	BC182		60	—	—	
	BC183		45	—	—	
	BC184		45	—	—	
Emitter–Base Breakdown Voltage (I_E = 100 μA, I_C = 0)		$V_{(BR)EBO}$	6.0	—	—	V
Collector Cutoff Current		I_{CBO}				nA
(V_{CB} = 50 V, V_{BE} = 0)	BC182		—	0.2	15	
(V_{CB} = 30 V, V_{BE} = 0)	BC183		—	0.2	15	
	BC184		—	0.2	15	
Emitter–Base Leakage Current (V_{EB} = 4.0 V, I_C = 0)		I_{EBO}	—	—	15	nA

© Motorola, Inc. 1996

ELECTRICAL CHARACTERISTICS (T_A = 25°C unless otherwise noted) (Continued)

Characteristic		Symbol	Min	Typ	Max	Unit
ON CHARACTERISTICS						
DC Current Gain		h_{FE}				—
(I_C = 10 μA, V_{CE} = 5.0 V)	BC182		40	—	—	
	BC183		40	—	—	
	BC184		100	—	—	
(I_C = 2.0 mA, V_{CE} = 5.0 V)	BC182		120	—	500	
	BC183		120	—	800	
	BC184		250	—	800	
(I_C = 100 mA, V_{CE} = 5.0 V)	BC182		80	—	—	
	BC183		80	—	—	
	BC184		130	—	—	
Collector–Emitter On Voltage		$V_{CE(sat)}$				V
(I_C = 10 mA, I_B = 0.5 mA)			—	0.07	0.25	
(I_C = 100 mA, I_B = 5.0 mA)(1)			—	0.2	0.6	
Base–Emitter Saturation Voltage (I_C = 100 mA, I_B = 5.0 mA)(1)		$V_{BE(sat)}$	—	—	1.2	V
Base–Emitter On Voltage		$V_{BE(on)}$				V
(I_C = 100 μA, V_{CE} = 5.0 V)			—	0.5	—	
(I_C = 2.0 mA, V_{CE} = 5.0 V)			0.55	0.62	0.7	
(I_C = 100 mA, V_{CE} = 5.0 V)(1)			—	0.83	—	
DYNAMIC CHARACTERISTICS						
Current–Gain — Bandwidth Product		f_T				MHz
(I_C = 0.5 mA, V_{CE} = 3.0 V, f = 100 MHz)	BC182		—	100	—	
	BC183		—	120	—	
	BC184		—	140	—	
(I_C = 10 mA, V_{CE} = 5.0 V, f = 100 MHz)	BC182		150	200	—	
	BC183		150	240	—	
	BC184		150	280	—	
Common Base Output Capacitance (V_{CB} = 10 V, I_C = 0, f = 1.0 MHz)		C_{ob}	—	—	5.0	pF
Common Base Input Capacitance (V_{EB} = 0.5 V, I_C = 0, f = 1.0 MHz)		C_{ib}	—	8.0	—	pF
Small–Signal Current Gain		h_{fe}				—
(I_C = 2.0 mA, V_{CE} = 5.0 V, f = 1.0 kHz)	BC182		125	—	500	
	BC183		125	—	900	
	BC184		240	—	900	
	BC182A		125	—	260	
	BC182B		240	—	500	
Noise Figure		NF				dB
(I_C = 0.2 mA, V_{CE} = 5.0 V, R_S = 2.0 kΩ, f = 1.0 kHz)						
(I_C = 0.2 mA, V_{CE} = 5.0 V, R_S = 2.0 kΩ, f = 1.0 kHz, f = 200 Hz)	BC184		—	2.0	4.0	
	BC182		—	2.0	10	
	BC183		—	2.0	10	
	BC184		—	2.0	4.0	

1. Pulse Test: Tp 300 s, Duty Cycle 2.0%.



Figure 1. Normalized DC Current Gain



Figure 2. “Saturation” and “On” Voltages



Figure 3. Current–Gain — Bandwidth Product



Figure 4. Capacitances



Figure 5. Base Spreading Resistance

PACKAGE DIMENSIONS





SECTION X–X

NOTES:
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
2. CONTROLLING DIMENSION: INCH.
3. CONTOUR OF PACKAGE BEYOND DIMENSION R IS UNCONTROLLED.
4. DIMENSION F APPLIES BETWEEN P AND L. DIMENSION D AND J APPLY BETWEEN L AND K MINIMUM. LEAD DIMENSION IS UNCONTROLLED IN P AND BEYOND DIMENSION K MINIMUM.

	INCHES		MILLIMETERS	
DIM	MIN	MAX	MIN	MAX
A	0.175	0.205	4.45	5.20
B	0.170	0.210	4.32	5.33
C	0.125	0.165	3.18	4.19
D	0.016	0.022	0.41	0.55
F	0.016	0.019	0.41	0.48
G	0.045	0.055	1.15	1.39
H	0.095	0.105	2.42	2.66
J	0.015	0.020	0.39	0.50
K	0.500	—	12.70	—
L	0.250	—	6.35	—
N	0.080	0.105	2.04	2.66
P	—	0.100	—	2.54
R	0.115	—	2.93	—
V	0.135	—	3.43	—

STYLE 17:
PIN 1. COLLECTOR
2. BASE
3. EMITTER

CASE 029–04
(TO–226AA)
ISSUE AD

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. “Typical” parameters can and do vary in different applications. All operating parameters, including “Typicals” must be validated for each customer application by customer’s technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and Ⓜ are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

How to reach us:
USA/EUROPE: Motorola Literature Distribution;
P.O. Box 20912; Phoenix, Arizona 85036. 1–800–441–2447

MFAX: RMFAX0@email.sps.mot.com – TOUCHTONE (602) 244–6609
INTERNET: http://Design–NET.com

JAPAN: Nippon Motorola Ltd.; Tatsumi–SPD–JLDC, Toshikatsu Otsuki,
6F Seibu–Butsuryu–Center, 3–14–2 Tatsumi Koto–Ku, Tokyo 135, Japan. 03–3521–8315

HONG KONG: Motorola Semiconductors H.K. Ltd.; 8B Tai Ping Industrial Park,
51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852–26629298